

0xDB + KA*5	0 ÷ 4	Parameter Type of alarm (chapter 12.6)	R/W
0xDC + KA*5	0 ÷ 5000	Parameter Alarm hysteresis	R/W
0xDD + KA*5	-9999 ÷ 19999	Parameter Alarm value	R/W
0xDE + KA*5	1 ÷ 100	Parameter Output signal value - percentage [%]	R/W
0xDF + KA*5	1 ÷ 3600	Parameter Output signal pulse period - number of seconds [s]	R/W
0xEF (239)	0 ÷ 1	Parameter Alarm sound signal	R/W
0xF0 (240)	0 ÷ 1	Parameter Email alarm notifications (chapter 12.6.1)	R/W
0xF1 (241)	0 ÷ 6	Parameter Function of the F button (chapter 12.9)	R/W
0xF2 (242)	0 ÷ 1	Parameter Buttons and touch sound (chapter 12.9)	R/W
0xF3 (243)	0 ÷ 3	Parameter Password protection (chapter 12.9)	R/W
0xF4 (244)	0 ÷ 9999	Parameter Password (chapter 12.9)	R/W
0xF5 (245)	0 ÷ 9999	Parameter Identification number ID (chapter 12.3)	R/W
0xF6 (246)	0 ÷ 60	Parameter Screen backlight time (chapter 12.7)	R/W
0xF7 (247)	20 ÷ 100	Parameter Brightness of the screen (chapter 12.7)	R/W
0xF8 (248)	0 ÷ 60	Parameter Channel and group auto switch time (chapter 12.7)	R/W
0xF9 (249)	0 ÷ 11	Parameter Chart time range (chapter 12.7)	R/W
0xFA (250)	0 ÷ 1	Parameter Language (chapter 12.7)	R/W
0xFB (251)	60 ÷ 14400	Parameter Radio scanning interval (chapter 12.8) - number of seconds [s]	R/W
0xFC (252)	0 ÷ 6	Parameter Radio channel number (chapter 12.8)	R/W
0xFD (253)	0 ÷ 1	Parameter USB operation mode (chapter 12.8)	R/W
0xFE (254)	0 ÷ 1	Parameter RS485 operating mode (MODBUS-RTU) (chapter 12.8)	R/W
0xFF (255)	1 ÷ 247	Parameter MODBUS-RTU slave address (chapter 12.8)	R/W
0x100 (256)	0 ÷ 6	Parameter Baud rate for the RS485 (chapter 12.8)	R/W
0x101 (257)	0 ÷ 3	Parameter Ethernet operation mode (chapter 12.8)	R/W
0x102 (258)	80 ÷ 32767	Parameter UDP and TCP port (chapter 12.8)	R/W
0x103 (259)	0x0000 ÷ 0xFFFF	Octet4 (HB), Octet3 (LB)	Parameter IP address (chapter 12.8)
0x104 (260)	0x0000 ÷ 0xFFFF	Octet2 (HB), Octet1 (LB)	
0x105 (261)	0x0000 ÷ 0xFFFF	Octet4 (HB), Octet3 (LB)	Parameter Subnet mask (chapter 12.8)
0x106 (262)	0x0000 ÷ 0xFFFF	Octet2 (HB), Octet1 (LB)	
0x107 (263)	0x0000 ÷ 0xFFFF	Octet4 (HB), Octet3 (LB)	Parameter Default gate (chapter 12.8)
0x108 (264)	0x0000 ÷ 0xFFFF	Octet2 (HB), Octet1 (LB)	
0x109 (265)	0x0000 ÷ 0xFFFF	Octet4 (HB), Octet3 (LB)	Parameter DNS server (chapter 12.8)
0x10A (266)	0x0000 ÷ 0xFFFF	Octet2 (HB), Octet1 (LB)	
0x10B ÷ 0x10C	0	not used	R/W
0x10D (269)	0 ÷ 1	Parameter Dynamic DNS server client (chapter 12.8.1)	R/W
0x10E (270)	0 ÷ 60	Parameter Website automatic refresh time (chapter 12.8)	R/W

21. USER'S NOTES
